

# Omni-Directional Whip Antenna

## FME-Female Connector

BT459860

**Wideband whip antenna for signal booster systems. Connects directly to the booster. Improves reception inside a room or small building.**

- Omni-directional whip antenna
- Adjustable right-angle antenna connects directly to booster
- 2.1dB Gain
- FME-Female connector
- 50 Ohm
- Wide band 2G, 3G, 4G LTE (698 - 2155 MHz)



### ELECTRICAL STUFF

Product Specifications may change without prior notice.

Item No.	BT459860	
Frequency Range	MHz	698 - 960   1700 - 2700
Gain	dBi	3 dB
Input Impedance	ohm	50
VSWR	≤2.0	
Bandwidth (MHz)	118/140	
Power Rating	Watts	10
Radiation	Omni-Directional	
Polarization Type	Vertical	

### MECHANICAL STUFF

Connector Type	FME-Female	
Material	Rubber	
Antenna Length	in	7.125
Antenna Weight	36.85 gm	1.23 oz
Operating Temperature	-22°F to +140°F	
Ground Plane	Built-in Ground Plane	



**QUESTIONS? CALL US TODAY**  
888-987-2658

✉ [sales@boltontechnical.com](mailto:sales@boltontechnical.com)  
 🌐 [www.boltontechnical.com](http://www.boltontechnical.com)

📍 5010 Wright Road, Suite 115  
Stafford, TX, 77477

