Omni-Directional Whip Antenna

N-Male Connector





BT151632

The perfect partner for your cell phone signal booster. This simple whip antenna will replace or upgrade the antenna that comes with your booster. Get up to 2.1 dBi gain for better reception wherever your booster is installed.

- · Omni-directional whip antenna
- · Adjustable right-angle antenna connects directly to booster
- · 2.1dB Gain
- · N-Male connector
- •50 Ohm
- · Wide band 2G, 3G, 4G LTE (698 2155 MHz)



ELECTRICAL STUFF		Product Specifications may change without prior notice.		
Item No.	BT151632			
Frequency Range	MHz	698 - 787 824 - 896 1710 - 2155		
Gain	dBi	2±1dB		
Input Impedance	ohm	50		
VSWR		2.0		
Bandwidth (MHz)	89/72/445			
Power Rating	Watts	10		
Radiation	Omni-Directional			
Polarization Type	Vertical			

MECHANICAL STUFF				
Connector Type	N-Male			
Antenna Base	ABS			
Antenna Length	in	9.25		
Antenna Weight	34.86 grams	1.23 oz		
Operating Temperature	-22°F to +167°F			
Ground Plane	Built-in Ground Plane			











